



INT TD10

Touchless Body Temperature
Measurement

As the number of cases has been increasing and the geographical has been widening, the novel coronavirus outbreak has raised grave concern about public health and personal hygiene.

The disease can occasionally cause symptoms like high fever, and INT TD10 is an infrared thermometer with pass count and alarm count. It can assist in body temperature measurement at the forehead and wrist of passengers. If the temperature detected is over 37.3°C or any other value set by the administrative user, INT TD10 will raise an alarm to inform the guards.

FEATURES

- Touchless body temperature measurement
- High temperature alarm
- No installation required
- Support temperature compensation
- Customizable height of temperature sensor from the ground
- Pass count and alarm count

SPECIFICATIONS

Power Requirements	AC 100 ~ 120V/200 ~ 240V
Electrical Current	900mA
Working Temperature	0°C ~ 40°C (32°F ~ 104°F)
Working Environment	Indoor
Dimensions (L*W*H)	1700 * 200 * 300
Packing Dimensions (L*W*H)	1750 * 350 * 250
Weight with Packing (kg)	14.9
Temperature Sensor Type	IR temperature sensor
Temperature Measurement Time	≤1s
Temperature Measurement Point	Forehead or wrist
Temperature Measurement Distance	40mm
Height of Temperature Sensor from the Ground	1500mm (customizable)
Temperature Measurement Deviation	±0.3°C(±0.54°F)
Temperature Range	20°C ~ 40°C (68°F ~ 104°F)
Interval Between Temperature Measurement	2s

* This product is not suit for environment with strong light or high temperature. It is recommended to use this product indoors.